L_p -Stability of a Class of Volterra Systems

Michaël Anton(ie) van Wyk, *Member, IEEE*, Guanrong Chen, *Life Fellow, IEEE*

Abstract—This paper presents some new and explicit stability results for Volterra systems from two different approaches. The first approach is based on monomial domination of the Volterra system’s memoryless output nonlinearity and the second on its Lipschitz-norm. The former yields more widely applicable results, but introduces nonconvexity in the signal spaces for certain parameter values.

Index Terms—Lipschitz-norm, L_p -norm, nonconvex set, stability, Volterra series, Volterra system.

I. INTRODUCTION

The stability of Volterra systems has been a focal research topic for both natural scientists [1] and engineers [2]–[4], with a renewed interest when novel applications and results emerge [5]. A state-of-the-art review on the use of Volterra series for modeling of nonlinear systems is presented in [6], which seems to suggest a declining interest in the stability analysis of Volterra systems in recent years.

This paper communicates new and explicit stability results for Volterra systems. Specifically, the L_p -stability of a general continuous-time nonlinear system, described by a Volterra series expansion, is studied. The equivalent discrete-time results follow in a straightforward manner by standard modifications to those for the continuous-time versions.

Following the seminal work of Boyd and Chua [7], on Volterra systems with fading memory, we are able to derive concise stability criteria. When a fading-memory Volterra system’s memoryless output nonlinearity is not continuous, its Lipschitz-norm may not exist. However, it might still be bounded by some Lipschitz-continuous mapping, enabling one to derive a stability criterion. For the case of monomial domination, this approach produces nonconvex ϵ -balls in the signal spaces of interest for certain parameter values. On the other hand, imposing the more stringent requirement of Lipschitz-continuity on the output nonlinearity ensures the existence of its Lipschitz-norm, thus preventing nonconvex sets from entering the analysis. The stability criterion so obtained necessarily applies to a smaller class of systems. These two approaches yield different stability bounds, thus providing more versatility by allowing selection of the more appropriate of the two, for a given application.

Financial Support Acknowledgment: This work was supported in part by the Carl and Emily Fuchs Foundation’s Chair in Systems and Control Engineering at the University of the Witwatersrand, Johannesburg, South Africa and by the Hong Kong Research Grants Council under GRF Grant CityU11200317.

Michaël A. van Wyk is with the School of Electrical and Information Engineering, The University of the Witwatersrand, Johannesburg, South Africa and City University of Hong Kong, Hong Kong SAR, China (e-mails: anton.vanwyk@wits.ac.za, mavanwyk@gmail.com).

Guanrong Chen is with the Department of Electrical Engineering, City University of Hong Kong, Hong Kong SAR, China (e-mail: eegchen@cityu.edu.hk).

II. L_p -STABILITY OF VOLTERRA SYSTEMS

This paper focuses on the class of fading-memory Volterra systems, which includes a vast range of engineering applications. Furthermore, their specific structure allows concise analytical expressions to be obtained.

First, three distinct cases are considered: a monomial nonlinearity, a general monomially dominated nonlinearity and a Lipschitz-continuous nonlinearity. After a discussion of the results obtained, three more general cases are presented to pave the way toward analysis of multiple-input, multiple-convolution and multiple-output Volterra systems.

Case 1: Consider the following single-input single-convolution Volterra system: a Linear Time-Invariant (LTI) system with input signal x and impulse response $g \in L_1[0, \infty)$ that feeds into a memoryless nonlinearity of the form $(\cdot)^v$, for a given $0 < v < \infty$. Its output is described by

$$y = (g * x)^v, \quad (1)$$

where $*$ represents convolution. Even though the power function is memoryless, the output y possesses memory with respect to x due to the convolution featuring in (1). Young’s convolution inequality [8, Th. 9.1] states that

$$\|g * x\|_p \leq \|g\|_1 \|x\|_p, \quad (2)$$

for all $1 \leq p \leq \infty$, with $\|\cdot\|_p$ the standard L_p -norm on $[0, \infty)$. Using inequality (2), one obtains

$$\begin{aligned} \|y\|_q^{\frac{1}{v}} &\equiv \|(g * x)^v\|_q^{\frac{1}{v}} = \left(\int_0^\infty |(g * x)^v(\tau)|^q d\tau \right)^{1/vq} \\ &= \left(\int_0^\infty |g * x|^{vq}(\tau) d\tau \right)^{1/vq} \\ &\equiv \|g * x\|_{vq} \\ &\leq \|g\|_1 \|x\|_{vq}, \end{aligned}$$

for all $1 \leq vq \leq \infty$, or alternatively, $1/v \leq q \leq \infty$. It follows that the Volterra system, described by (1), is finite-gain input-output stable from $L_{vq}[0, \infty)$ to $L_q[0, \infty)$ for every $v > 0$ and every q satisfying $1/v \leq q \leq \infty$, both fixed.

It is interesting to note that, for $v > 1$, the lower bound of q , namely $1/v$, is less than one. However, for $1/v < q < 1$, the L_q -norm’s triangle inequality is violated, causing every ϵ -ball in the output signal space $L_q[0, \infty)$ to be *nonconvex* [9], [10]. On the other hand, if q is taken to be greater than or equal to one, then, for sufficiently small $0 < v < 1$, it follows that $vq < 1$ so that every ϵ -ball in the input signal space $L_{vq}[0, \infty)$ is *nonconvex*.

The consequences of a Lebesgue exponent¹ strictly between zero and one are far reaching concerning the operator theory

¹Parameter p is called the *Lebesgue exponent* of the *Lebesgue space* L_p .

applicable to this Lebesgue space (see [11]). For example, any linear functional on this Lebesgue space is identically zero [12], implying that only nonlinear functionals on this space are worth studying.

Case 2: Consider a more general single-input single-convolution Volterra system, with a memoryless output nonlinearity described by a bounded and measurable real-valued function $h(\cdot)$ that is dominated by the monomial $(\cdot)^v$, that is,

$$|h(u)| \leq |u|^v, \quad \text{for all } u \in \mathbb{R}.$$

This implies that $h(0) = 0$ and so it follows immediately that

$$\|h(g * x)\|_q \leq \|g\|_1^v \|x\|_{vq}^v, \quad (3)$$

for all $1 \leq vq \leq \infty$, based on the results derived for Case 1 above.

Interestingly, in this last inequality, the norm of the nonlinear function $h(\cdot)$ does not appear on the right-hand side. From (3), it follows that the single-input single-convolution Volterra system with memoryless output nonlinearity being any measurable function $h(\cdot)$, dominated by the power- v function, is finite-gain input-output stable from $L_{vq}[0, \infty)$ to $L_q[0, \infty)$ for every $v > 0$ and every $1/v \leq q \leq \infty$, both fixed.

Note that the above remarks about the nonconvexity of ε -balls in the Lebesgue spaces also apply here.

Case 3: To further extend the previous results, assume $h(\cdot)$ to be a Lipschitz-continuous memoryless nonlinearity. Consider the Lipschitz-norm defined by

$$\|h\|_{\text{Lip}(p,q)} = \|h\|_\infty + \sup_{u_1 \neq u_2} \frac{\|h(u_1) - h(u_2)\|_q}{\|u_1 - u_2\|_p},$$

for fixed $1 \leq p, q \leq \infty$, where $\|\cdot\|_\infty$ denotes the standard sup-norm [13],[14]. Here, the subscript $\text{Lip}(p, q)$ is introduced merely to explicitly indicate this norm's dependency on the domain and range spaces of $h(\cdot)$.

For every constant function $h(\cdot)$, the first term in $\|\cdot\|_{\text{Lip}(p,q)}$ satisfies $\|h\|_\infty = |h(0)|$ while the second term there, i.e. the slope of $h(\cdot)$, is identically zero.² This yields the following expression for the Lipschitz-norm:

$$\|h\|_{\text{Lip}(p,q)} = |h(0)| + \sup_{u_1 \neq u_2} \frac{\|h(u_1) - h(u_2)\|_q}{\|u_1 - u_2\|_p}.$$

For the purpose of the discussion that follows, it is noted that

$$\|h\|_{\text{Lip}(p,q)} \geq |h(0)| + \frac{\|h(u_1) - h(u_2)\|_q}{\|u_1 - u_2\|_p},$$

for arbitrary but fixed arguments u_1 and u_2 on the right-hand side of the inequality, yielding

$$\begin{aligned} \|h(u_1) - h(u_2)\|_q \\ \leq (\|h\|_{\text{Lip}(p,q)} - |h(0)|) \|u_1 - u_2\|_p. \end{aligned} \quad (4)$$

²The quotient, in the expression for the Lipschitz-norm $\|h\|_{\text{Lip}(p,q)}$ of $h(\cdot)$, is a *seminorm*, which vanishes for every constant function $h(\cdot)$.

Since the intermediate signals, u_1 and u_2 , are the result of convolutions, the above inequality can be expressed as

$$\begin{aligned} \|h(g * x_1) - h(g * x_2)\|_q \\ \leq (\|h\|_{\text{Lip}(p,q)} - |h(0)|) \|g * x_1 - g * x_2\|_p \\ = (\|h\|_{\text{Lip}(p,q)} - |h(0)|) \|g * (x_1 - x_2)\|_p \quad (\text{Linearity}) \\ \leq (\|h\|_{\text{Lip}(p,q)} - |h(0)|) \|g\|_1 \|x_1 - x_2\|_p, \end{aligned} \quad (5)$$

for some input signals x_1 and x_2 , after applying (2).

For the case of $h(0) = 0$, with $h(\cdot)$ not necessarily power- v dominated, by setting $x_2 = 0$, one has

$$\|h(g * x_1)\|_q \leq \|h\|_{\text{Lip}(p,q)} \|g\|_1 \|x_1\|_p, \quad (6)$$

for all $1 \leq p, q \leq \infty$. Therefore, for arbitrary but fixed $1 \leq p, q \leq \infty$, a single-input single-convolution Volterra system with a memoryless output nonlinearity $h(\cdot)$ that has a finite Lipschitz-norm $\|\cdot\|_{\text{Lip}(p,q)}$ and $h(0) = 0$, but is not necessarily dominated by the power- v function, is finite-gain input-output stable from $L_p[0, \infty)$ to $L_q[0, \infty)$.

At this juncture, a caution is not to underestimate the role of the assumption $h(0) = 0$. To see this, note that assuming $h(0) \neq 0$ and $x_2 \equiv 0$ in (5) gives

$$\begin{aligned} \|h(g * x_1) - h(0)1(\cdot)\|_q \\ \leq (\|h\|_{\text{Lip}(p,q)} - |h(0)|) \|g\|_1 \|x_1\|_p, \end{aligned} \quad (7)$$

where $1(t) := 1$ for all $t \in [0, \infty)$. If one now attempts to apply the norm inequality $\|z_1\| - \|z_2\| \leq \|z_1 - z_2\|$, derived from the triangle inequality, to the left-hand side, then

$$\begin{aligned} \|h(g * x_1)\|_q - |h(0)| \|1(\cdot)\|_q \\ \leq \|h(g * x_1) - h(0)1(\cdot)\|_q. \end{aligned} \quad (8)$$

This is problematic because, for the standard $L_q[0, \infty)$ space, when $q \neq \infty$, one would have that $\|1(\cdot)\|_q = \infty$ because $1(\cdot)$ is not in the space $L_q[0, \infty)$. Therefore, one cannot isolate the term $\|h(g * x_1)\|_q$ by combining (5), (7) and (8) in the hope of deriving an upper bound for it.

However, for the case of $q = \infty$, one has $\|1(\cdot)\|_\infty = 1$ and, therefore, one can now isolate the term $\|h(g * x_1)\|_\infty$ by combining (5), (7) and (8), so as to obtain

$$\begin{aligned} \|h(g * x_1)\|_\infty \\ \leq (\|h\|_{\text{Lip}(p,\infty)} - |h(0)|) \|g\|_1 \|x_1\|_p + |h(0)|. \end{aligned}$$

Consequently, the Volterra system considered here is finite-gain input-output stable, even for $h(0) \neq 0$.

Now, returning to (6), with $h(0) = 0$ therein, and setting $p = q$, one obtains

$$\|h(g * x)\|_q \leq \|h\|_{\text{Lip}(q,q)} \|g\|_1 \|x\|_q, \quad (9)$$

for an arbitrary input signal $x \in L_q[0, \infty)$ with $1 \leq q \leq \infty$.

Comparing (9) with (3), it can be seen that the root (or powers) of v has been eliminated by including the factor consisting of the Lipschitz-norm of $h(\cdot)$ on the right-hand side. It is important to note that (9) and (3) give two alternative but *not* equivalent criteria for assessing the L_p -stability of a Volterra system. In fact, (3) does *not* require $h(\cdot)$ to be Lipschitz-continuous; it even applies to the extreme case of $h(\cdot)$ being L_q -integrable but nowhere-differentiable.

Case 4: Consider a two-input two-convolution Volterra system described by the equation

$$y := h(g_1 * x_1, g_2 * x_2),$$

where the real-valued memoryless nonlinearity $h(\cdot, \cdot)$ is assumed to be Lipschitz-continuous and $g_1, g_2 \in L_1[0, \infty)$. The Lipschitz-norm considered here is

$$\|h\|_{\text{Lip}(p_1, p_2, q)} := |h(0, 0)| + \sup_{(u_1, s_1) \neq (u_2, s_2)} \frac{\|h(u_1, s_1) - h(u_2, s_2)\|_q}{\|(u_1, s_1) - (u_2, s_2)\|_{p_1, p_2}},$$

for fixed $1 \leq p_1, p_2, q \leq \infty$, and the direct-sum norm³ $\|\cdot\|_{p_1, p_2}$, taken to be

$$\|(u_1, s_1) - (u_2, s_2)\|_{p_1, p_2} := \|u_1 - u_2\|_{p_1} + \|s_1 - s_2\|_{p_2}.$$

For arbitrary direct-sum signals (u_1, s_1) and (u_2, s_2) , one has

$$\|h(u_1, s_1) - h(u_2, s_2)\|_q \leq (\|h\|_{\text{Lip}(p_1, p_2, q)} - |h(0, 0)|) (\|u_1 - u_2\|_{p_1} + \|s_1 - s_2\|_{p_2}).$$

Substituting

$$u_i := g_1 * x_{1i} \quad \text{and} \quad s_i := g_2 * x_{1i}, \quad i = 1, 2,$$

into this inequality then yields

$$\begin{aligned} & \|h(g_1 * x_{11}, g_2 * x_{21}) - h(g_1 * x_{12}, g_2 * x_{22})\|_q \\ & \leq (\|h\|_{\text{Lip}(p_1, p_2, q)} - |h(0, 0)|) (\|g_1\|_1 \|x_{11} - x_{12}\|_{p_1} \\ & \quad + \|g_2\|_1 \|x_{21} - x_{22}\|_{p_2}), \end{aligned}$$

where the linearity of convolution and inequality (2) were used.

Now, assuming that $h(0, 0) = 0$ holds and then setting $x_{12} = x_{22} \equiv 0$, finally gives

$$\|h(g_1 * x_1, g_2 * x_2)\|_q \leq \|h\|_{\text{Lip}(p_1, p_2, q)} \|g_1\|_1 \|x_1\|_{p_1} + \|h\|_{\text{Lip}(p_1, p_2, q)} \|g_2\|_1 \|x_2\|_{p_2}, \quad (10)$$

for arbitrary input signals $x_1 \in L_{p_1}[0, \infty)$ ($1 \leq p_1 \leq \infty$, fixed) and $x_2 \in L_{p_2}[0, \infty)$ ($1 \leq p_2 \leq \infty$, fixed) and for arbitrary $1 \leq q \leq \infty$, fixed. Thus, if the Lipschitz-norm of $h(\cdot)$ is finite, then this Volterra system is finite-gain input-output stable from the direct-sum space $L_{p_1}[0, \infty) \oplus L_{p_2}[0, \infty)$ to $L_q[0, \infty)$.

Case 5: If the inputs are joined by setting $x_2 = x_1$ in Case 4, then one obtains a single-input two-convolution Volterra system. From (10), it then follows that

$$\|h(g_1 * x_1, g_2 * x_1)\|_q \leq \|h\|_{\text{Lip}(p_1, p_2, q)} \|g_1\|_1 \|x_1\|_{p_1} + \|h\|_{\text{Lip}(p_1, p_2, q)} \|g_2\|_1 \|x_1\|_{p_2},$$

where, in general, $p_1 \neq p_2$. Under the assumption that $h(\cdot)$ has a finite Lipschitz-norm, the resulting Volterra system is finite-gain input-output stable from $L_{p_1}[0, \infty) \cap L_{p_2}[0, \infty)$ to $L_q[0, \infty)$. If, in addition $p_2 = p_1 \equiv p$, then (10) reduces to

$$\begin{aligned} & \|h(g_1 * x_1, g_2 * x_2)\|_q \\ & \leq \|h\|_{\text{Lip}(p_1, p_2, q)} (\|g_1\|_1 + \|g_2\|_1) \|x_1\|_p \end{aligned}$$

and this Volterra system is finite-gain input-output stable from $L_p[0, \infty)$ to $L_q[0, \infty)$.

³There are many other direct-sum norms to choose from.

Now, imposing power- v domination extends the earlier results.

Case 6: The last two more general cases easily generalize to a Volterra system with an arbitrary number of inputs, an arbitrary number of convolutions associated with each input, and an arbitrary number of outputs for both the cases of power- v domination and of Lipschitz-continuity of the output nonlinear memoryless mapping.

Finally, note that the exact same arguments presented above apply to the discrete-time case, thus producing equivalent results.

III. CONCLUSION

This paper presented some new and explicit stability results for Volterra systems when the output nonlinearity possesses a Lipschitz-norm as well as for the more general case of a measurable, monomially dominated output nonlinearity. These two approaches yield alternative but not equivalent stability criteria, thus providing more versatility by allowing selection of the more appropriate of the two for a given application.

ACKNOWLEDGMENT

M.A. van Wyk's research chair in System and Control Engineering is financially supported by the Carl and Emily Fuchs Foundation.

The authors wish to thank Mr. A.M. McDonald for proof-reading and assisting with the submission process.

REFERENCES

- [1] S. D. Tuljapurkar and J. S. Semura, "Stability of Lotka-Volterra Systems," *Nature*, vol. 257, pp. 388–389, Oct. 1975.
- [2] I. W. Sandberg, "Volterra-like Expansions for Solutions of Nonlinear Integral Equations and Nonlinear Differential Equations," *IEEE Trans. Circ. Syst.*, vol. 30, no. 2, pp. 68–77, Feb. 1983.
- [3] I.W. Sandberg, "Multilinear Maps and Uniform Boundedness," *IEEE Trans. on Circ. Syst.*, vol. 32, no. 4, pp. 332–336, Apr. 1985.
- [4] I.W. Sandberg, "Criteria for the Stability of p -Linear Maps and p -Powers," *Nonlinear Anal.*, vol. 15, no. 1, pp. 69–84, 1990.
- [5] A. Borys, "Analysis of Harmonic Distortion in Analog Circuits with the use of Volterra Series and Kronecker Products," *Int. J. Microelectron. Comput. Sci.*, vol. 7, no. 1, pp. 1–9, Jan. 2016.
- [6] C.M. Cheng, Z.K. Peng, W.M. Zhang and G. Meng, "Volterra-Series-Based Nonlinear System Modeling and its Engineering Applications: A State-of-the-Art Review," *Mech. Syst. Signal Process.*, vol. 87, pp. 340–364, Nov. 2017.
- [7] S. Boyd and L.O. Chua, "Fading Memory and the Problem of Approximating Nonlinear Operators with Volterra Series," *IEEE Trans. Circ. Syst.*, vol. 32, no. 11, pp. 1150–1161, Nov. 1985.
- [8] R.L. Wheeden and A. Zygmund, *Measure and Integral: An Introduction to Real Analysis*, CRC Press, 2015.
- [9] E.H. Lieb and M. Loss, *Analysis*, American Mathematical Society, 1997.
- [10] M.M. Day, "The Spaces L^p with $0 < p < 1$," *Bull. Amer. Math. Soc.*, vol. 46, no. 10, pp. 816–823, 1940.
- [11] N.J. Kalton, "Linear Operators on L_p for $0 < p < 1$," *Trans. Amer. Math. Soc.*, vol. 259, no. 2, pp. 319–355, Jun. 1980.
- [12] B. Farkas, "On the duals of L_p spaces with $0 < p < 1$," *Acta Math. Hungar.*, vol. 98, no. 1-2, pp. 71–77, 2003.
- [13] R.J.P. de Figueiredo and G. Chen, *Nonlinear Feedback Control Systems: An Operator Theory Approach*, Academic Press, 1993.
- [14] J.M. Ortega and W.C. Rheinboldt, *Iterative Solution of Nonlinear Equations in Several Variables*, Academic Press, 1970.
- [15] J. Ponstein, "Seven Kinds of Convexity," *SIAM Review*, vol. 9, no. 1, pp. 115–119, Jan. 1967.
- [16] H.J. Greenberg and W.P. Pierskalla, "A Review of Quasi-Convex Functions," *Operations Research*, vol. 19, no. 7, pp. 1553–1570, Nov.-Dec. 1971.