An all-optical spatial light modulator for reconfigurable silicon photonic circuits: supplementary material

ROMAN BRUCK,¹ KEVIN VYNCK,² PHILIPPE LALANNE,² BEN MILLS,³ DAVID J. THOMSON,³ GORAN Z. MASHANOVICH,³ GRAHAM T. REED,³ AND OTTO L. MUSKENS^{1,*}

¹ Physics and Astronomy, Faculty of Physical Sciences and Engineering, University of Southampton, Southampton SO17 1BJ, UK

² LP2N, UMR 5298, CNRS – IOGS – Univ. Bordeaux, 33400 Talence, France

³ Optoelectronics Research Centre, University of Southampton, Southampton SO17 1BJ, UK

*Corresponding author: o.muskens@soton.ac.uk

Published 5 April 2016

This supplementary material to “An all-optical spatial light modulator for field-programmable silicon photonic circuits” <http://dx.doi.org/10.1364/optica.3.000396> describes the methods used and gives additional information regarding the tolerance of the position and strength of the perturbation pattern, as well as the lifetime of free carriers in the multimode interference device. © 2016 Optical Society of America

<http://dx.doi.org/10.1364/optica.3.000396.s001>

1. Tolerance of the beam steering effect

In order to create a tailored intensity profile at the output plane of the multimode interference (MMI) region, a specific pattern of perturbations in the spatial refractive index profile of the MMI device is needed and we develop this pattern using an optimization process as described in the main text. Here, we investigate the tolerance of the device performance with respect to variations of certain parameters of the perturbation pattern.

Figure (S1(a)) shows the electric field map with the numerically optimized perturbation pattern as presented in Fig. 2 of the main text. This pattern was optimized for a refractive index difference Δn of -0.25 and gives a transmission of 92.5% in the upper MMI output. Deviating from the design value for the refractive index contrast naturally reduces device performance. However, as is revealed in Fig. (S1(b)), a transmission of better than 90% is achieved for the same pattern for an almost 0.1-wide Δn window.

Further, we numerically studied the effect of pattern displacement on the device performance. Figure (S2(c)) and (S1(d)) give the transmission through the upper (c) and lower (d) output of the MMI, respectively, as function of the pattern displacement in propagation direction (Δz) and lateral direction (Δx). Clearly, device performance is more sensitive with respect to lateral displacement as this directly influences the mode power

coupling. Similarly, we investigated the effect of pattern displacement experimentally, as summarized in Fig. (S2).

2. Measurement off the free carrier lifetime

We analyzed the temporal behavior of the excited free carriers in the MMI region. For this purpose, we excited the full width of the MMI over a length of 3.5 μm (see Fig (S3(a))). With this approach we ensured that all MMI modes would be attenuated by the same factor. The induced absorption is linear to the number of free carriers. By scanning the delay time between probe and pump pulses, we can analyze the concentration of free carriers in the time domain (see Fig (S3(b))). We apply an exponential fit to the measured data and find the free carrier lifetime for this system of $\tau = 173.5 \pm 0.7$ ps.

3. Methods

Optical setup. The laser system used for the presented experiments is an amplified 800 nm Ti-Sapphire laser coupled with an optical parametric amplifier (OPA) providing 150 fs pulses at a 250 kHz repetition rate. The system gives a frequency doubled output at 400 nm, used as the pump, and an idler output of the parametric amplifier which was tuned to 1550 nm for the presented measurements. In our setup (see Fig. 1(a)) the probe pulses are in-coupled by the use of a grating coupler from a

Fig. (S1), Robustness of beam steering against variations of parameters. (a) Simulated electric field map of the MMI with the numerically optimized perturbation pattern, as presented in Fig. 2 in the main text. (b) Transmission ($\lambda = 1550$ nm) into the two output waveguides of the perturbed MMI as function of refractive index change in the perturbation pattern (top output: red, bottom output: blue). Excellent device performance (> 90% for the top output and < 2% in the bottom output) can be achieved for an almost 0.1-wide Δn -window. (c,d) Transmission into upper (c) and lower (d) output as a function of the displacement of the pattern ($\Delta n = 0.25$).

singlemode fibre, using TE polarization. The transmitted light of one output of the MMI-device is end-face coupled into a singlemode fibre and subsequently to a spectrometer. The pump beam is expanded to a diameter of about 15 mm and spatially modulated by a Texas Instruments DLP7000 digital micro-mirror device (DMD) with a resolution of 1024×768 physical pixels and a pixel pitch of $13.6 \mu\text{m}$. For our experiments, we combine 10×10 physical pixels of the DMD to one logical pixel (see below). The main text addresses logical pixels only. The imaging system comprises a 40 cm lens and a $100\times 0.5\text{NA}$ Mitutoyo microscope objective, to reduce the pattern size from the DMD by a factor 200, thus translating the $136 \mu\text{m}$ edge length logical pixels into spots of about 700 nm on the MMI-device surface. We note that the 18 experiments presented in Figs. 3-5 have not been preselected and represent a set of 18 consecutive experiments. For these experiments the output port for which $\Delta T/T$ was maximized was alternated to prove the symmetry of the device and our approach. In the analysis, the change in transmission $\Delta T/T$ is used rather than the absolute transmission to correct for inherent experimental variations in laser intensity and for differences in the throughput of the individual output waveguides and cleaved end facets. A complete experimental optimization process requires around 15 minutes.

MMI-device. The MMI 1×2 power splitter was optimized using 3D FIMMWAVE simulations and fabricated from a 220 nm -thick silicon layer on top of a $2 \mu\text{m}$ -thick SiO_2 layer employing the deposition of a silica hard mask, DUV-193-nm lithography and HBr dry etching of the MMI structure [1]. The MMI region has a design length of $31.875 \mu\text{m}$ and a width of $6 \mu\text{m}$. The separation of the two MMI output waveguides is $3.14 \mu\text{m}$ (center-to-center). Single mode 400 nm -wide waveguides are tapered to $1 \mu\text{m}$ at the MMI boundaries, ensuring an adiabatic size conversion of the fundamental mode over a $10 \mu\text{m}$ -distance.

Refractive index modulation. In our experiments, we measured an average pump fluence of $64 \text{ pJ}/\mu\text{m}^2$ incident onto the

MMI surface. Based on our previous study [2], this, on average, changes the real part of the refractive index in the bulk silicon under the pumped area by -0.25 . Larger refractive index modulations up to -0.5 are possible without damaging the silicon. However, in the presented experiments, we were limited by the total pump power provided by the laser system, which has to be delivered over the whole area of the MMI.

Fully-vectorial modal simulations (a-FMM). The simulations presented in Figs. 1-3, and in the Supplementary Material, were performed using an in-house fully-vectorial frequency-domain Fourier Modal method (a-FMM) [3]. This method calculates the modes in a Fourier basis, using a supercell method and perfectly-matched layers. It relies on a scattering-matrix formalism to describe accurately the coupling between modes propagating in the input waveguide, MMI, and output waveguides. Simulations were performed in 2D with a wavelength-dependent effective index (2.85 at a wavelength of $1.55 \mu\text{m}$) to account for the vertical confinement of the fundamental TE-mode of the 220 nm -thick silicon slab. Out-of-plane scattering produced by the refractive index modulations in the cladding is expected to be weak due to the small refractive index change ($\Delta n = -0.25$), thus we expect that 2D simulations can accurately predict the device performance. One simulation typically takes 1-3 seconds with a personal computer, thereby allowing rapid investigations of MMIs. MMI design parameters were used for the simulations. To reproduce the experimental beam steering effect presented in Fig. 3, we performed a parametric study of the device performance, optimizing the lateral and longitudinal position of the experimental perturbation pattern. The pattern position was therefore the only free parameter.

Experimental optimization process. *Influence of laser shot noise.* During experimental optimisation processes, $\Delta T/T$ before and after flipping a pixel can only be determined with certain accuracy due to laser shot noise. This unavoidably leads to the acceptance of a small number of pixels at the beginning of the optimization process that do not physically contribute to the

Fig. (S2), Impact of DMD pattern displacement. (a) Spectra for both outputs of the MMI after an experimental optimization run. (b) SEM micrograph of the MMI overlaid with the pump pattern used for spectra presented in (a). (c,d) Measured change in transmission for upper (c) and lower (d) output as a function of the displacement of the pattern shown in (b).

Fig. (S3), Free carrier lifetime in the silicon MMI region. (a) We extract the carrier lifetime in silicon in the investigated device by projecting a five pixel (3.5 μm) wide vertical line of pump light over the whole width of the MMI area. (b) We measure the resulting absorption, that is negative $\Delta T/T$ as function of the delay time (red line). As the absorption is proportional to the number of free carriers, this measurement gives a reliable statement on the free carrier population as function of time. The dashed black line is an exponential fit of the form $\frac{\Delta T}{T} = a * e^{-t/\tau}$ with t being the delay time and τ the carrier lifetime. The fit parameters were determined as $a = -0.3609 \pm 0.006$ and $\tau = 173.5 \pm 0.7$ ps with a fitting range from 10 ps to 700 ps.

wavefront shaping process. We counteract this fact by positioning region 1 partly outside the MMI region allowing pixels being accepted due to laser noise without affecting the wavefront.

Choice of logical pixel size. In the presented experiments we combined 10×10 physical pixels of the DMD to one logical pixel. In theory, smaller logical pixels would allow for a finer control over the mode distribution. However, by reducing pixel size, the impact of individual pixels on $\Delta T/T$ is smaller and thus more difficult to detect in the presence of laser noise. We experimented with different logical pixel sizes (5×5 to 20×20 physical pixels), with 10×10 physical pixels giving the most reliable results without sacrificing device performance.

Advanced algorithms. In the main text, we present a comparatively simple optimization algorithm in order find an optimal perturbation pattern for the desired device characteristic. To further improve the quality of wavefront shaping, we also evaluated more advanced optimization algorithms in the experiments. In a first approach, we applied the presented

algorithm twice, using the end configuration of the first run as start configuration of the second run. This approach yielded only negligible return. Additionally, we investigated genetic algorithms, where DMD configurations found with the presented algorithm (parent-configurations) were combined and mutated to create new configurations (child-configurations). However, no significant improvement could be achieved due to the nature of the optimization problem and limitations in the experimental setup. Firstly, the optimization function is of high dimension and generally has many local maxima, that is that many different DMD configurations can satisfy a large $\Delta T/T$ increase. However, the same is not necessarily true for combinations from these patterns, strongly reducing the probability that child-configurations surpass their parent-configurations. Secondly, starting from already excellent results with the algorithm presented, only small improvements are expected, which are difficult to detect due to laser shot noise and require long averaging periods, eventually

increasing the optimization time beyond a point where the long-term stability of the used laser system can be guaranteed.

Running average on presented spectra. The spectra presented in Fig. 3(c) show a ripple structure with a period of about 0.6 nm, which is consistent with reflections from the cleaved end face at the end of the output waveguides. Hence we plot the measured spectra (thin lines) overlaid with a running average (thick lines), with an averaging window of ± 2.1 nm (± 25 spectral points provided by the spectrometer).

REFERENCES

- [1] D. J. Thomson, Y. Hu, G. T. Reed, and J. M. Fedeli, "Low Loss MMI Couplers for High Performance MZI Modulators," *Photon. Tech. Lett.* **22**, 1485-1487 (2010).
- [2] R. Bruck Ben Mills, B. Troia, D.J. Thomson, F.Y. Gardes, Y. Hu, G.Z. Mashanovich, V.M.N. Passaro, G.T. Reed, and O.L. Muskens, "Device-level characterization of the flow of light in integrated photonic circuits using ultrafast photomodulation spectroscopy," *Nature Photon.* **9**, 54–60 (2015).
- [3] E. Silberstein, P. Lalanne, J. P. Hugonin, and Q. Cao, "Use of grating theory in integrated optics," *J. Opt. Soc. Am. A.* **18**, 2865-2875 (2001).